


Multi Super DC Inverter

Tabuľky kombinovateľnosti

M20G-14HFN8-Q	1 vnútorný 2 Vnútorné		M20D-18HFN8-Q	1 vnútorný 2 Vnútorné		M30F-21HFN8-Q	1 vnútorný 2 Vnútorné 3 Vnútorné			
	9	9+9		9	9+9		9	9+9	9+9+9	
	12	9+12		12	9+12		12	9+12	—	
	18	—		18	12+12		18	9+18	—	
							—	12+12	—	
M30F-27HFN8-Q	1 vnútorný 2 Vnútorné		3 Vnútorné		M40E-28HFN8-Q	1 vnútorný 2 Vnútorné		3 Vnútorné 4 Vnútorné		
	9	9+9	12+12	9+9+9	9+12+12	9	9+9	12+18	9+9+9	
	12	9+12	12+18	9+9+12	12+12+12	12	9+12	12+24	9+9+12	
	18	9+18	—	9+12+12	—	18	9+18	18+18	9+9+18	
						24	9+24	—	9+12+12	
						—	12+12	—	12+12+12	
M40-36HFN8-Q	1 vnútorný		2 Vnútorné		3 Vnútorné		4 Vnútorné			
	9	9+9	18+18	9+9+9	9+18+18	9+9+9+9	12+12+12+12			
	12	9+12	—	9+9+12	12+12+12	9+9+9+12	12+12+12+18			
	18	9+18	—	9+9+18	12+12+18	9+9+9+18	—			
	24	9+24	—	9+9+24	12+12+24	9+9+12+12	—			
	—	12+12	—	9+12+12	12+18+18	9+9+12+18	—			
	—	12+18	—	9+12+18	—	9+12+12+12	—			
	—	12+24	—	9+12+24	—	9+12+12+18	—			
M50-42HFN8-Q	1 vnútorný		2 Vnútorné		3 Vnútorné		4 Vnútorné		5 Vnútorné	
	9	9+9	9+9+9	12+12+12	9+9+9+9	12+12+12+12	9+9+9+9+9	12+12+12+12+12		
	12	9+12	9+9+12	12+12+18	9+9+9+12	12+12+12+18	9+9+9+9+12	—		
	18	9+18	9+9+18	12+12+24	9+9+9+18	—	9+9+9+9+18	—		
	24	9+24	9+9+24	12+18+18	9+9+9+24	—	9+9+9+12+12	—		
	—	12+12	9+12+12	—	9+9+12+12	—	9+9+9+12+18	—		
	—	12+18	9+12+18	—	9+9+12+18	—	9+9+12+12+12	—		
	—	12+24	9+12+24	—	9+12+12+12	—	9+12+12+12+12	—		
	—	18+18	9+18+18	—	9+12+12+18	—	9+12+12+12+18	—		

